

**Note: If your SAP GUI version is lower than 7.40 then first upgrade it.**

**If Script file doesn't work, then follow below steps**

### **SOP for SAP LOGON PAD entry**

1. Make entries in hosts file of the local desktop under path

C:\Windows\System32\drivers\etc

10.201.219.39 erpprdapp.erp.bsnl.co.in erpprdapp

10.198.216.91 eccci.bsnl.co.in

10.201.219.59 eppprdapp eppprdapp.erp.bsnl.co.in

10.198.216.91 erpportal.bsnl.co.in

10.201.219.39	erpprdapp.erp.bsnl.co.in	erpprdapp
10.198.216.91	eccci.bsnl.co.in	
10.201.219.59	eppprdapp	eppprdapp.erp.bsnl.co.in
10.198.216.91	erpportal.bsnl.co.in	

2. Make entries in services file of the local desktop under path

C:\Windows\System32\drivers\etc

sapmsPRD 3601/tcp

sapmsEPP 3601/tcp

Put space in the file after the entry

sapmsPRD	3601/tcp
sapmsEPP	3601/tcp

Also either delete following entries or comment it with #

sapmsPRD 3600/tcp

sapmsPRD 3600/tcp
-------------------

3. Delete existing connections from SAP Logon PAD & close it  
Also delete all files from Common folder under path

C:\Users\%User%\AppData\Roaming\SAP\Common

4. Now open SAP GUI Logon pad ,if entry is not available then maintain the entries in the below sequence

Description : ECC HANA SOH

System ID : PRD

Message Server : erpprdapp.erp.bsnl.co.in:3601

Connection

Network

Code Page

Choose the connection type and change the system parameters as required. Delete the old description if you want the system to propose a description. The 'OK' button is activated once you have entered all required input data.


**Connection Type**

☒ Group/Server Selection

☐ Custom Application Server

**System Connection Parameters**

Description:	ECC HANA SOH
System ID:	PRD
Instance Number:	
SAProuter:	
Group/Server:	
Message Server:	erpprdapp.erp.bsnl.co.in:3601

 Enter the required data

- Click on the right side dropdown of Group/Server and select PUBLIC

Connection	Network	Code Page
------------	---------	-----------

Choose the connection type and change the system parameters as required. Delete the old description if you want the system to propose a description. The 'OK' button is activated once you have entered all required input data.


**Connection Type**

☒ Group/Server Selection

☐ Custom Application Server

**System Connection Parameters**

Description:	ECC HANA SOH
System ID:	PRD
Instance Number:	00
SAProuter:	
Group/Server:	PUBLIC
Message Server:	erpprdapp.erp.bsnl.co.in

 IP address=10.201.219.30 cannot be converted to the host name ( d:\depot\bas\753\_REL\fes\_770\_REL\src\fes\few\sapdpams\dpamsci.cpp,1489)

- Click on ok and entries will be saved.
- Close the SAP Logon Pad and reopen
- Double click on the newly created entry(ECC HANA SOH) in the SAP Logon Pad

ECC HANA SOH	PRD	PUBLIC	erpprdapp.erp.bsnl.co.in
--------------	-----	--------	--------------------------